CCS-7710: Cable for Nec 3510 and 5510 Spinwriter (1/97)

```
Revised:        1/28/97
Security:       Everyone
```

CCS-7710: Cable for Nec 3510 and 5510 Spinwriter (1/97)

```
=====================================================================
```

Article Created: 11 July 1985
Article Reviewed/Updated: 28 January 1997

```
TOPIC -------------------------------------------------------------
```

Listed below are the cable pinouts for connecting the CCS-7710 interface card to the Nec 3510 or 5510 Spinwriter printers.

```
DISCUSSION --------------------------------------------------------
```

```
Nec Spinwirter 3510
-------------------

CCS-7710                    NEC 3510 SPINWRITER

3 <---------------------> 3
4 <---------------------> 19
7 <---------------------> 7
                          6,8,20: Jumpered


Nec Spinwriter 5510
-------------------

CCS-7710                    NEC 5510 SPINWRITER

3 <---------------------> 3
4 <---------------------> 19
7 <---------------------> 7
                          5,6,8,20: Jumpered

CCS 7710 dip switch settings for Nec 5510
-----------------------------------------
All down except #3
```

NEC 5510 dip switch settings

All down except #4,7,8

NEC 510 front panel switch settings

Speed=h, parity=m, dup=f, set to remote.

* These cable are for use with the Apple IIe computer.

Article Change History:
28 Jan 1997 - Reviewed for technical accuracy, revised formatting.

Tech Info Library Article Number:1468